

## About this evaluation kit

To run MxNet2 server in this kit, there is no need for Matrix dongle. The mxnet2 server will always detect one virtual ( software ) dongle.

### Virtual Dongle Memory Fields

The values for the memory Field 1 through 5 can be set in the setting file which must exist in the same folder as MxNet2.exe and whose name must be mxnet2.dongle. The value for the memory field 3 is fixed to 3, no matter what value is set in the setting file.

The encryption key can also be set in the file. Refer to the sample setting file for detail.

### AppSlot

The only valid AppSlot is 3. LogIn/LogOut API must be called with AppSlot argument set to 3. When a different value is given, the APIs will return the error -177

### UserCode / Serial Number

The virtual dongle has UserCode 1234 and Serial Number 1234567890

Client API included is identical to the commercial version.